



## Amlogic Buildroot Openlinux Release Note

**AMLOGIC, Inc.**  
2518 Mission College Blvd  
Santa Clara, CA 95054  
U.S.A.  
[www.amlogic.com](http://www.amlogic.com)

AMLOGIC reserves the right to change any information described herein at any time without notice.  
AMLOGIC assumes no responsibility or liability from use of such information.

# Amlogic Openlinux Release Notes

---

## Content

<b>1. Basic Information.....</b>	<b>3</b>
1.1. INTRODUCTION.....	3
1.1.1. Kernel Version.....	3
1.1.2. List of Supported Drivers.....	3
1.2. CHIP INFORMATION.....	3
1.3. HOW TO GET CODE.....	4
1.4. REFERENCE PLATFORM.....	4
1.5. HOW TO BUILD CODE.....	5
1.5.1. Kernel Toolchain.....	5
1.5.2. Build.....	5
1.6. HOW TO UPGRADE.....	5
<b>2. Test Report.....</b>	<b>6</b>
2.1.VIDEO FORMAT TEST REPORT FOR GSTPLAYER.....	6
2.2.VIDEO FORMAT TEST REPORT FOR KMPLAYER.....	7
<b>3. Recent Changes.....</b>	<b>8</b>
<b>4. Known Issue.....</b>	<b>8</b>

## 1. Basic Information

### 1.1. Introduction

This document provides the Openlinux notes for Amlogic Linux BSP reference source code release running on Amlogic reference hardware. To obtain Amlogic Linux BSP reference source code, you will need to have an account to access Amlogic GIT source code repository.

#### 1.1.1. Kernel Version

Kernel version is 4.9.76:

```
commit 7bbc6ca4887794cc44b41412a35bdfbe0cbd1c50
Author: Greg Kroah-Hartman <gregkh@linuxfoundation.org>
Date:   Wed Jan 10 09:29:55 2018 +0100

Linux 4.9.76
```

#### 1.1.2. List of Supported Drivers

- 1) Timer / Interrupts
- 2) Clocks
- 3) Pinmux/GPIO/GPIO IRQ
- 4) Remote
- 5) Hdmi
- 6) UART
- 7) USB Host
- 8) CPU DVFS
- 9) System Thermal (IPA)
- 10) CPU Hotplug
- 11) SD/SDHC/SDXC
- 12) eMMC
- 13) eFuse
- 14) CEC
- 15) SARADC/ADCKEY
- 16) I2C
- 17) PWM
- 18) SDIO WiFi/USB WiFi
- 19) Bluetooth
- 20) LED
- 21) Ethernet
- 22) SecureOS
- 23) SecureBoot

## 1.2. Chip Information

Item	S905D2	S905X2
<b>CPU</b>	Quad Cortex-A53	Quad Cortex-A53
<b>Max CPU Freq.</b>	1.896G Hz	1.896G Hz
<b>GPU</b>	ARM Dvalin MP2	ARM Dvalin MP2
<b>Security</b>	TrustZone & TVP	TrustZone & TVP
<b>Memory</b>	DDR3/4 LPDDR3/4	DDR3/4 LPDDR3/4
<b>Video decoding</b>	4K H265&VP9&AVS2	4K H265&VP9&AVS2

# Amlogic Openlinux Release Notes

<b>Video Encoding</b>	1080P H264 H265	1080P H264 H265
<b>HDMI-Tx</b>	4K2K	4K2K
<b>Ethernet</b>	10/100M/1000M	10/100M
<b>AV output</b>	CVBS	CVBS
<b>IP License</b>	Dolby,DTS	Dolby,DTS

## 1.3. How to Get Code

### 1) repo command

You can download Linux BSP source code by running the following repo commands:

- **China openlinux server**

```
$ cd ~/<your-repo-dir>/
$ repo init -u ssh://git@openlinux.amlogic.com/buildroot/platform/manifest.git
$ repo init -m buildroot-openlinux-20180418.xml
$ repo sync
```

- **Overseas openlinux server**

```
$ cd ~/<your-repo-dir>/
$ repo init -u ssh://git@openlinux2.amlogic.com/buildroot/platform/manifest.git
$ repo init -m buildroot-openlinux-20180418.xml
$ repo sync
```

### 2) download tar package

You can download the tar package freely, but it has no git info:

```
$ wget -c
http://openlinux.amlogic.com:8000/download/ARM/filesystem/Linux_BSP/buildro
ot_openlinux_kernel_4.9_fbdev_20180418.tar.gz
$ tar xvzf buildroot_openlinux_kernel_4.9_fbdev_20180418.tar.gz
```

## 1.4. Reference Platform

- **U200(S905D2)**  
EMMC,WIFI AP6398S,DDR 2GB
- **U211(S905X2)**  
EMMC,WIFI AP6398S,DDR 2GB

# Amlogic Openlinux Release Notes

## 1.5. How to Build Code

### 1.5.1. Kernel Toolchain

The cross-compile tool used for kernel 4.9 is : gcc-linaro-6.3.1-2017.02-x86\_64\_aarch64-linux-gnu/, and it should be pre-installed before kernel build.

```
aarch64-linux-gnu-gcc -v
gcc version 6.3.1 20170109 (Linaro GCC 6.3-2017.02)
```

### 1.5.2. Build

You can find corresponding Buildroot setenv config and kernel config for the reference hardware by doing the following:

#### 1) Mbox U200

```
. buildroot/build/setenv.sh
choose mesong12a_u200_32_release config option
make
Note: Do not use make -jN here as Buildroot does not support top-level parallel
make. This does not mean that Buildroot does not support parallel compilation, but
just that it will handle this inside the Buildroot compilation system.
```

#### 2) Mbox U211

```
. buildroot/build/setenv.sh
choose mesong12a_u211_32_release config option
make
Note: Do not use make -jN here as Buildroot does not support top-level parallel
make. This does not mean that Buildroot does not support parallel compilation, but
just that it will handle this inside the Buildroot compilation system.
```

The upgrade file aml\_upgrade\_package.img will be generated in output/[config\_build\_folder]/images/.

## 1.6. How to Upgrade

- For Windows: Upgrade with USB burn tool. (version 2.1.5 or upper)
- For Linux: Upgrade with bash script aml\_update\_whole\_package.sh. Make sure usb driver has been installed correctly.
  - 1) plugin power cable, at the same time, hold down the POWER key.
  - 2) plugin the usb cable within 5 seconds.
  - 3) cd the script directory.
  - 4) ./aml\_update\_whole\_package.sh path/to/aml\_upgrade\_package.img.

## 2. Test Report

### 2.1.Video Format Test Report For GSTplayer

Extension	Codec Detail	Tested Resolution	S805X
.3g2	H263	704x576	Support
.3gp	MPEG-4 Visual	640x480	Support
	H263	704x576	Support
	MPEG-4	320x240	Support
.asf	WMV3	320x240	Support
.avi	AVC	1920x1080	Support
	DivX5	1280x720	Support
	M-JPEG	1024x576	Support
	MS MPEG-4 V1	352x218	Support
	RealMagic MPEG-4	720x480	Support
		720x576	Support
	h264	1920x1080	Support
	FF mpeg MPEG4	640x480	Support
	XVID	640x480	Support
	S-Mpeg 4 v3	720x400	Support
	DivX3	720x576	Support
	DivX4	1920x1080	Support
	.dat	MPEG-1	352x288
.divx	DivX5	1280x720	Support
.f4v	AVC(H264)	1280x720	Support
.flv	Sorenson Spark	1920x1080	Support
.mp4	AVC(H264)	1920x1080	Support
	HEVC(H265)	1920x1080	Support
	4K HEVC(4K H265)	4096x2304	Support
	H263	176x144	Support
	MPEG-4 Visual	640x480	Support
.m2ts	AVC	1920x1080	Support
.m2v	MPEG-2	480x576	Support
.m4v	AVC	1280x720	Support
.mkv	WMV3	1280x720	Support
	MPEG-4 Visual	1920x1080	Support
	AVC	1920x1080	Support
	4K HEVC(4K H265)	3840x2160	Support
.mov	MPEG-4 Visual	1280x720	Support
	mjpa	640x480	Support
	H263	320x240	Support
	M-JPEG	640x480	Support
	AVC	1920x1080	Support
	MPEG-4 Visual	640x480	Support
.mpeg	MPEG-2	1920x1080	Support
	MPEG-1	720x576	Support
.mts	AVC	1440x1080	Support
.ogm	DivX5	640x336	Support

## Amlogic Openlinux Release Notes

	XVID	640x480	Support
.tp	MPEG-2	1920x1088	Support
.ts	HEVC(H265)	1920x1080	Support
	4K HEVC(4K H265)	4096x2304	Support
	MPEG-1	1920x1080	Support
	AVC	1920x1080	Support
	MPEG-2	1920x1080	Support
.vob	MPEG-2	720x576	Support
.h265	HEVC(H265)	1920x1080	Support
4K	AVC(H264)	4096x2304	Support
	HEVC(H265)	4096x2304	Support

### 2.2.Video Format Test Report For Kmpayer

Extension	Codec Detail	Tested Resolution	S805X
.3g2	H263	704x576	Support
.3gp	MPEG-4 Visual	640x480	Support
	H263	704x576	Support
	MPEG-4	320x240	Support
.asf	WMV3	320x240	Support
.avi	AVC	1920x1080	Support
	DivX5	1280x720	Support
	M-JPEG	1024x576	Support
	MS MPEG-4 V1	352x218	Support
	RealMagic	720x480	Support
	MPEG-4	720x576	Support
	h264	1920x1080	Support
	FF mpeg	640x480	Support
	MPEG4	640x480	Support
	XVID	640x480	Support
	S-Mpeg 4 v3	720x400	Support
.dat	DivX3	720x576	Support
	DivX4	1920x1080	Support
	MPEG-1	352x288	Support
	DivX5	1280x720	Support
.divx	DivX5	1280x720	Support
.f4v	AVC(H264)	1280x720	Support
.flv	Sorenson Spark	1920x1080	Support
.mp4	AVC(H264)	1920x1080	Support
	HEVC(H265)	1920x1080	Support
	4K HEVC(4K H265)	4096x2304	Support
	H263	176x144	Support
	MPEG-4 Visual	640x480	Support
.m2ts	AVC	1920x1080	Support
	VC-1	1920x1080	Support
.m2v	MPEG-2	480x576	Support
.m4v	AVC	1280x720	Support
.mkv	WMV3	1280x720	Support
	MPEG-4 Visual	1920x1080	Support
	AVC	1920x1080	Support
	4K HEVC(4K	3840x2160	Support

## Amlogic Openlinux Release Notes

	H265)		
.mov	MPEG-4 Visual	1280x720	Support
	mjpa	640x480	Support
	H263	320x240	Support
	M-JPEG	640x480	Support
	AVC	1920x1080	Support
	MPEG-4 Visual	640x480	Support
.mpeg	MPEG-2	1920x1080	Support
	VC-1	1920x1080	Support
	MPEG-1	720x576	Support
	WMV1	320x240	Support
.mts	AVC	1440x1080	Support
.ogm	DivX5	640x336	Support
	XVID	640x480	Support
.PMP	H264	480x272	Support
.rmvb	RealVideo4	1920x1080	Not Support
.tp	MPEG-2	1920x1088	Support
.ts	HEVC(H265)	1920x1080	Support
	4K HEVC(4K H265)	4096x2304	Support
	MPEG-1	1920x1080	Support
	AVC	1920x1080	Support
	AVS	720x576	Support
	AVS+	720x576	Support
	MPEG-2	1920x1080	Support
.vob	MPEG-2	720x576	Support
.mvc	mvc	1920x1080	Support
.h265	HEVC(H265)	1920x1080	Support
4K	AVC(H264)	4096x2304	Support
	HEVC(H265)	4096x2304	Support

### 3. Recent Changes

- 1) Support S905X2&S905D2
- 2) Support HDMI 2.2
- 3) Support SPICC
- 4) Support HS200 mode for eMMC
- 5) Optimize wifi/di/usb/hdmi
- 6) wifi throughput data improve

### 4. Known Issue

- 1) No web browser
- 2) Video pressure test has some problem